

### Set-up of ZigBee Controller for PhilipsHue

1. Ensure that the device isn't connected to any other network or has been removed from existing networks
2. If necessary, create a "room", in which the controller should be used
3. Start the search function for luminaires in the Hue app
4. Press the programme key on the controller 5 times in a row
5. If the learning process is successful, the connected light flashes 5 times in quick succession and the controller appears in the app
6. The device can now be used and configured via the Hue app

### Set-up of ZigBee Controller for Alexa (ZigBee Hub)

1. Ensure that the device isn't connected to any other network or has been removed from existing networks
2. Start the search function for devices in the Alexa app
3. Press the programme key on the controller 5 times in a row
4. If the learning process is successful, the connected light flashes 5 times in quick succession and the controller appears in the app
5. The device can now be used and configured via the Alexa app

### Reset the controller to factory settings

Resetting the controller is not necessary during normal operation. A reset is required if the controller shall join a new network.

1. Short press "Prog." key for 5 times continuously or re-power on the device for 5 times at least min. 2 seconds in time continuously if the "Prog." key is not accessible.
2. Connected light flashes 3 times for successful reset.



If the device is already at factory default setting, there is no indication when factory reset again.